

PART NUMBER	RATED VOLTS	KVAR	HORSE POWER	AMPS	HEIGHT	WIDTH	DEPTH	ENCL TYPE	WATTS LOSS	WEIGHT	WEIGHT with Fuse Monitor
HGP0005AW3S0000	480	1.2	5	7.6	33.24	33	13.73	3R	150	100	102
HGP0008AW3S0000	480	3	7.5	11	33.24	33	13.73	3R	150	105	107
HGP0010AW3S0000	480	3	10	14	33.24	33	13.73	3R	175	112	114
HGP0015AW3S0000	480	5	15	21	33.24	33	13.73	3R	250	125	127
HGP0020AW3S0000	480	6	20	27	33.24	33	13.73	3R	275	125	127
HGP0025AW3S0000	480	8	25	34	33.24	33	13.73	3R	250	130	132
HGP0030AW3S0000	480	10	30	40	33.24	33	13.73	3R	300	144	146
HGP0040AW3S0000	480	15	40	52	37.58	39.15	13.73	3R	500	220	222
HGP0050AW3S0000	480	15	50	65	37.58	39.15	13.73	3R	550	229	231
HGP0060AW3S0000	480	20	60	77	37.58	39.15	13.73	3R	675	239	241
HGP0075AW3S0000	480	25	75	96	37.58	39.15	13.73	3R	650	246	248
HGP0100AW3S0000	480	30	100	124	37.58	39.15	13.73	3R	750	269	271
HGP0125AW3S0000	480	40	125	156	37.58	39.15	13.73	3R	1000	289	291
HGP0150AW3S0000	480	45	150	180	52.58	39.07	17.73	3R	1200	400	402
HGP0200AW3S0000	480	60	200	240	52.58	39.07	17.73	3R	1600	470	472
HGP0250AW3S0000	480	75	250	302	53.86	45.14	21.73	3R	1800	550	552
HGP0300AW3S0000	480	90	300	361	53.86	45.14	21.73	3R	2100	615	617
HGP0350AW3S0000	480	105	350	414	53.86	45.14	21.73	3R	2200	655	667
HGP0400AW3S0000	480	120	400	477	65.77	57.13	26.32	3R	2600	985	987
HGP0450AW3S0000	480	135	450	515	65.77	57.13	26.32	3R	2800	995	997
HGP0500AW3S0000	480	150	500	590	65.77	57.13	26.32	3R	3100	1000	1012
HGP0600AW3S0000	480	180	600	720	65.77	57.13	26.32	3R	2700	1224	1237
HGP0700AW3S0000	480	210	700	840	65.77	57.42	26.32	3R	2900	1400	1402
HGP0800AW3S0000	480	240	800	960	65.77	57.42	26.32	3R	3000	1584	1586
HGP0900AW3S0000	480	270	900	1080	80.22	72.06	30	3R	3300	3032	3034

\*Note- Products with fuse monitor will have "G" replace "S" in part number